



# SUPPORT - SERVICE



Etic Telecom provides the 1:1 NAT feature (namely: 1:1 Network Address Translation) on its 3 product families: [IPL](#), [RAS](#) and [XSLAN](#). This solution allows you to simply interconnect a machine to an industrial network without changing the factory IP address of this machine.



## B.E.S.D. Benelux B.V.

Industrieterrein "De Leemskulen"  
Wilhelminahof 7 – 8, 5751 GJ Deurne  
Postbus 203, 5750 AE Deurne  
The Netherlands

T. +31 (0)493 316 554

E. [info@besd.nl](mailto:info@besd.nl)

i. [www.besd.nl](http://www.besd.nl)

KvK. 50025619


BTW. NL.8225.04.571.B01

## Application note

### Starting with 1:1 NAT

- The 1:1 NAT solution
- Configuring the @IP WAN
- Configuring the @IP LAN
- Configuring the 1:1 NAT
- Hotline support during your test
- Virtual showroom

Latest update **09/14/2018**



The 1:1 NAT solution simply interconnects a machine to an industrial network without changing the factory IP address of this machine.  
It is sufficient to insert between the machine and the rest of the industrial network an IPL / RAS configured for an address translation.

In the « Setup » section, select « WAN interface » and give to the Etic Telecom router an IP address which is available in the Industrial network (for example: 192.168.10.128)

In the « Setup » section, select « LAN interface » => « Ethernet and IP » and give to Etic Telecom router an IP address which is available in the Machine network (for example: 192.168.3.128).

In the « Setup » section, select « Network > 1:1 NAT > Add/Edit a 1:1 NAT rule » enter the 2 IP@ to set up the translation (ex: @ 192.198.10.129 translated to @ 192.168.3.1).

> Home > Setup > Network > 1:1 NAT > Add/Edit a 1:1 NAT rule

Save Cancel Page has unsaved changes

Enabled	<input checked="" type="checkbox"/>
WAN on which apply the rule	Ethernet WAN ▾
WAN IP to add	192.198.10.129
LAN IP to map on WAN	192.168.3.1

Feel free to contact +33 4 76 04 20 05 or [hotline@etictelecom.com](mailto:hotline@etictelecom.com).

By surfing on our WEB site [www.etictelecom.com](http://www.etictelecom.com) (Support/Virtual Showroom) you can learn how to configure most of our products.

The following login and password may be requested: login: "etic", password: "demo".

The screenshot shows the Etic Telecom website with a green header bar. The header includes the Etic Telecom logo, navigation links for Qui sommes-nous?, Produits, Solutions, Support, Actualités, Contact, and Espace client, and language links for FR | EN. Below the header, a green banner reads "SHOWROOM VIRTUEL" and "Accédez à l'ensemble des produits Etic Telecom.". On the left, a sidebar titled "Sélectionnez une gamme de produits" lists product categories: Boîtiers d'Accès Machines (gamme RAS), Routeurs (gamme IPL), and Extenseurs d'Ethernet (gamme XS+). On the right, a sidebar titled "Sélectionnez un produit" lists specific products: IPL-E / Routeur Firewall pour Intranet and IPL-DAC / Routeur ADSL avec backup Cellulaire. At the bottom left is the Etic Telecom logo, and at the bottom right is contact information: 13, chemin du Vieux Chêne, 38240 Meylan, Tél. 04 76 04 20 00, Fax. 04 76 04 20 01, and the website [www.etictelecom.com](http://www.etictelecom.com). A page number "3" is at the bottom left, and a footer note "DOC\_MPR\_IPL\_Prise en main solution NAT 1 :1\_A" is at the bottom right.